

600W Portable Power Station

Description

The Zeconex Portable Power Station is a rechargeable battery-powered generator. Equipped with AC outlet, DC carport and USB charging ports, the Zeconex Power Station brings ideal emergency power for appliances like mini-fridge, air pump, laptop, and more!

A compact Devices such as laptops, LED lights, drones, mini fridges and projectors can be powered by the Zeconex power station for extended periods of time.



Application

- Home healthcare/Home Backup
- Outdoor Adventures
- Emergency Preparedness



US

EU

AU

UK

UNIVERSAL



Specification

Capacity :595.2Wh(19.2V, 31Ah); 186000mAh	Waveform:Sine wave
Battery Cell Type: LiFePO4 (3600+ Full Life Cycles)	LED Lighting:Full Bright / Half Bright / SOS Flashing Mode
2* AC Output :110V or 230V/600W(Rated); 1200W(Peak)	Input:12~30V / 100W Max
2* DC Output :12V/10A	Warranty:24 months
USB-C Output:PD 60W Max	Weight:19.29lb (8.75kg)
USB-A Output :5V/3A; 9V/2A; 12V/1.5A (18W Max)	Size:325*294*319 mm(12.8*11.58*12.6 Inch)
Color/Logo:Customized	Working Temperature: 0~45°C

Information

600W Portable Power Station's Advantages over Similar Products:

- Automotive-grade lithium batteries, Charging and discharging cycles around 3600 cycles;
- Support charging for the small device while discharging, no matter which way you charge this power station;
- (Battery Management System (BMS))protect your devices from overload, over current, short-circuit, over-temperature,etc;
- Equipped with more AC ports compared with others, more convenient to charge your devices at the same time;
- The input port size of the generator is DC7909, which can match most solar panels. We suggest choosing our Solar generator, which has a directly welded power cord with a 7909 port, that's more efficient. 23% high conversion efficiency than others.

About the item:

【Larger Smart Display】



【Five Ways to Recharge & Fast Charging】



【Function Description】



【Application】



【Package】



OEM/ODM

